Marque 2 M165


User Guide



Contents


What's in the Box **3** Headset Overview 4 Pairing 5 Pair First Time 5 Pair Another Phone 5 Charge **6** Fit **7** Adjust the Fit 7 The Basics 8 Make/Take/End Calls 8 Mute 8 Adjust the Volume 8 Stream Audio 8 More Features 9 Save Power 9 Decipher the Lights 9 Hear it Whisper 9 Disable Voice Commands 9 Technical Specifications 10

What's in the Box






Headset





Headset Overview




Ċ	Power button
	Call button
1	Charge port
-)0(-	Headset LED (indicator light)
●)/型	Volume/Mute button

Pairing

Pair First Time

The first time you power on your headset, it begins the pairing process.

1 Put the headset on and turn it on.



- iPhone and Android[™] Smartphones Follow the voice-guided pairing instructions.
- Other phones Use your phone's menu to:
- ² While the headset LEDs are flashing red and white, activate Bluetooth[®] on your phone and set it to search for new devices.
- 3 Select "PLT_M165."
- 4 If your phone asks, enter four zeros (0000) for the passcode or accept the connection. The indicator light → stops flashing red and white once successfully paired.


Pair Another Phone

Multipoint technology lets you pair a second phone and answer calls from either phone.

- 1 Power on your headset.
- 2 $\,$ Press and hold the Call button S until the indicator light $\stackrel{_\sim}{\to} \stackrel{_\sim}{}$ flashes red and white or you hear "pairing."
- While the indicator light is flashes red and white, activate Bluetooth on your phone and set it to search for new devices.
- 4 Select "PLT_M165."
- 5 If your phone asks, enter four zeros (0000) for the passcode or accept the connection. The indicator light →∞ stops flashing red and white once successfully paired.

Charge

Your new headset has enough power to pair and make a few calls. It takes two hours to fully charge the headset; the indicator light turns off once charging is complete.




Adjust the Fit


- The universal-fit eartip has a thin loop that bends to gently tuck into the contours of either ear.
- 1 Rotate the eartip on the headset or add the optional clip-on earloop to adjust the fit.



2 Replace the gel eartip with one of the two alternate sizes, if it feels loose or tight in your ear.



The Basics



Make/Take/End Calls

Answer a call

Choose:

- Say "answer" after call is announced, or
- lacksquare Tap the Call button lacksquare

Answer a second call

First, tap the Call button S to end current call, then tap the Call button S again to answer new call.

End a call Tap the Call button ${}^{\textcircled{}}$ to end current call.

Reject a call

Choose:

- · Say "ignore" after call is announced, or
- Press Call button [©] for 2 seconds

Call back last call

To dial your last number you dialed, double-tap the Call button @.

Voice dial (phone feature)

Press the Call button S for 2 seconds, wait for phone prompt and then tell the phone to dial the name of a stored contact.

Mute You can mute the microphone during a conversation.

During a call, tap the Volume/Mute Ψ/Ψ until you hear "mute on" or "mute off." While the microphone is muted, an alert repeats every 15 minutes.

Adjust the Volume Tap the Volume/Mute Ψ/Ψ button to cycle through preset levels.

Stream Audio Streaming audio is controlled using your phone, but when a call rings, the audio automatically pauses to allow you to answer or ignore the call. Once the call is ignored or ends, the streaming audio is resumed.

More Features

Save Power	lf you leave your headset powered on but out of range of your paired phone for more than 90 minutes, your headset will conserve its battery power by entering into a DeepSleep [™] mode.
	Once back in range with your phone, tap the Call button ${ m \textcircled S}$ to exit DeepSleep mode. If your phone is also ringing, tap the Call button ${ m \^ S}$ again to answer your call.
Decipher the Lights	Your headset has an indicator light 👾 that flashes in response to a change in status or after a button press.
	Some examples of what you will see are: • Solid red until charging complete and then off
	Flashing red and white during pairing
	 Triple red flash when less than 10 minutes of talk time
	Triple white flash at incoming call
Hear it Whisper	Your headset tells you about status changes in English. For example:
	"Power on"
	"Pairing successful"
	"Talk time (x) hours"
	"Mute on"
	"Lost connection"
	"Recharge headset"
Disable Voice Commands	This headset only speaks and understands English. If you prefer to use the Call button to answer or reject calls, you can disable the voice commands "answer" or "ignore."
	With the headset powered on, simultaneously press the Call ${ m C}$ and Volume ${ m I}$ buttons until you see the indicator light flash white two times. Repeat these steps to reactivate the commands.

Technical Specifications

Up to 7 hours*
Up to 11 days*
7 grams
 Activates when paired headset is out of range for over 90 minutes
 Provides up to 180 days* of battery readiness
Use one headset to answer calls from either of two paired Bluetooth phones
Micro USB charging
Rechargeable, non-replaceable lithium-ion polymer
90 minutes for full charge
On-screen for iPhone, enabled by Find MyHeadset [™]
v3.0
Advanced Audio Distribution Profile (A2DP), Wideband Hands Free (HFP) Profile 1.6 and Headset (HSP) Profile 1.2
32°F – 104°F (0 – 40°C)

NOTE * Performance is dependent upon battery and may vary by device.

NEED MORE HELP?

www.plantronics.com/support

plantronics.

Simply Smarter Communications™

Plantronics, Inc.

Plantronics BV

345 Encinal StreetSouSanta Cruz, CA 95060ScoUnited States213

South Point Building C Scorpius 140 2132 LR Hoofddorp, Netherlands

© 2012 Plantronics, Inc. All Rights Reserved. Bluetooth is a registered trademark of Bluetooth SIG, Inc. and any use by Plantronics is under license. All other trademarks are the property of their respective owners.

Patents US 5,712,453; Patents Pending 89142-06 (09.12)

plantronics.